



前視圖

背視圖



- | | | |
|-------------|--------------------|------------------|
| ● A 硬碟LED燈 | ● E 警示LED燈 | ● I USB-C埠(僅供電用) |
| ● B 硬碟托盤把手 | ● F 電源LED燈 | ● J 風扇轉速開關 |
| ● C 硬碟托盤彈出鍵 | ● G 風扇 | ● K 電源開關 |
| ● D 靜音開關 | ● H USB-C埠(40Gbps) | |

包裝內容物：

- US2-B4 x1
- 速安裝手冊 x1
- USB3.2 Type-C to Type-C 線 (白色, 僅供DC供電使用) x1
- USB4 Type-C to Type-C 線 (黑色) x1
- 零件包

請注意：

- 請檢查產品和所有隨附附件是否有損傷或缺失零件。如果您遇到任何問題，請聯絡您的產品供應商。
- 如需更多資訊、資源和下載相關資料，請造訪STARDOM 官方網站www.STARDOM.com.tw。



v0.1 (Feb. 2026)

1

LED燈號說明

狀態	電源LED燈狀態
DC電源充足	藍燈恆亮
DC電源不足	紅燈恆亮

請注意：

- 請使用支援 PD 5V/3A 的電源或將 US2 連接到 Thunderbolt™ 3/4/5 主機以獲得足夠的電力。
- 紅色電源 LED 亮起時，請勿開啟電源開關。

狀態	硬碟LED燈狀態	故障LED燈	蜂鳴器
硬碟閒置	藍燈恆亮	----	----
資料存取中	藍燈閃爍	----	----
無硬碟	紅燈恆亮	----	----
溫度過高 (60°C)	----	紅燈閃爍	鳴叫
風扇異常	----	紅燈閃爍	鳴叫

硬體安裝


請參照下列步驟安裝 US2-B4：

1. 解開硬碟托盤：使將托盤彈出按鈕向右推，然後將硬碟托盤拉出。




2

2. 取下托盤上蓋：轉開硬碟托盤上蓋的螺絲並將上蓋取下。



3. 安裝M.2 NVMe SSD：轉開M.2 NVMe SSD固定螺絲，裝入M.2 NVMe SSD，然後重新鎖緊螺絲。



4. 重新裝上托盤上蓋：裝上硬碟托盤上蓋並用螺絲將其固定。
5. 連接纜線：使用隨附的USB線連接US2-B4與PC/Mac。黑色線用於資料傳輸，白色線用於電源供應。
6. 開啟電源：請開啟系統電源，作業系統應會自動偵測硬碟。
7. 格式化硬碟：如果必要，請依照作業系統指示格式化硬碟。

請注意：

- 請在啟動 US2 之前將 US2 連接到 PC/Mac (開機狀態)，否則 US2 將處於睡眠模式。

3

使用前注意事項

1. 使用正確的 USB 線 - 黑色 USB 線用於資料傳輸，白色 USB 線用於電源供電。
2. 備份資料 - 確保所有重要文件都有備份。
3. 接地 - 透過接地防止靜電釋放。
4. 拔掉電源 - 安裝前關閉電腦並拔掉電源插頭。
5. 使用無靜電表面 - 避免在地毯或導電表面上工作。
6. 閱讀說明 - 開始之前檢查所有步驟。
7. 安全移除 - 在關閉 US2 或移除 USB 連接之前，請務必透過作業系統安全移除US2。

感謝您選擇 STARDOM 產品！

請注意，本手冊中的資訊在出版時是正確的，但產品規格在出貨前可能已變更。有關最新規格與更新，請造訪 www.STARDOM.com.tw 或聯絡您的經銷商。

如果您對 STARDOM 產品有任何疑問，或是要取得最新的產品手冊或軟體更新，請發送電子郵件到 supporting@raidontek.com



4

US2-B4 Quick Installation Guide

Product Diagrams and Package Contents

Front View

Rear View



- | | | |
|------------------------------------|------------------------------|--------------------------------------|
| A Disk LED | E Alarm LED | I USB-C Port (For Power Only) |
| B Disk Tray Ejection Button | F Power LED | J Fan Speed Adjust Switch |
| C Disk Tray Handle | G Fan | K Power Switch |
| D Mute Button | H USB-C Port (40Gbps) | |

Package Contents:

- US2-B4 x1
- Quick Installation Guide x1
- USB3.2 Type-C to Type-C Cable (White, For DC Power Supply Only) x1
- USB4 Type-C to Type-C Cable (Black) x1
- Accessories

Please Note:

- Check the product and all included accessories for defects or missing parts. If you encounter any issues, contact your product supplier.
- For additional information, resources, and downloads, please visit the STARDOM official website at www.STARDOM.com.tw.



1

v0.1 (Feb. 2026)

Disk LED Status Guide

Status	Power LED Status
DC Power Sufficient	Blue light always On
DC Power Insufficient	Red light always On

Please Note:

- Please use the adapter supports PD 5V/3A or connect US2 to Thunderbolt™ 3/4/5 host to get sufficient power.
- Do not turn on the power switch if the Red power LED lights On.

Status	Disk LED Status	Alarm LED	Buzzer
Disk Idle	Blue light always On	----	----
Data Accessing	Blue light Flashing	----	----
No Disk	Red light Flashing	----	----
Over Temp. (60°C)	----	Red light always On	On
Fan Failed	----	Red light always On	On

Hardware Installation Guide


Follow these steps to install the US2-B4:

- 1. Unlock the Disk Tray:** Push the tray ejection button to the right, and pull the Disk Tray out.




2

- 2. Remove the Tray Cover:** Unscrew the upper cover of the Disk Tray.



- 3. Install the M.2 NVMe SSD:** Remove the M.2 NVMe SSD securing screw. Insert the M.2 NVMe SSD, and then re-secure it using the screw.



- 4. Reassemble the Disk Tray:** Close the upper cover of the Disk Tray and secure it with the screws.
- 5. Insert the Disk Tray:** Place the Disk Tray back into the US2-B4 unit.
- 6. Connect the Cables:** Use the included cable to connect the US2-B4 and PC/Mac.
- 7. Power On:** Turn on the system; the OS should auto-detect the disk.
- 8. Format Disk:** Follow OS prompts to format the disk if necessary.

Please Note:

- The US2-B4 operates on USB bus power by default. If you need to use the 5 V DC input for additional power, connect the USB-C 4.0 cable first, then plug in the 5V DC adapter.

3

Precautions Before Use

- 1. Use Correct USB Cable** – The Black USB cable is for data transmission and the White one is for DC power.
- 2. Backup Data** – Ensure you have a backup of all important files.
- 3. Ground Yourself** – Prevent static discharge by grounding yourself.
- 4. Unplug Power** – Turn off and unplug your computer before installation.
- 5. Use a Static-Free Surface** – Avoid working on carpets or conductive surfaces.
- 6. Read Instructions** – Review all steps before starting.
- 7. Safely Remove** – Always safely removed US2 through the operating system before turning it off or remove the USB connection.

Thank you for choosing STARDOM products!

Please note that the information in this manual was accurate at the time of publication, but product specifications may have changed prior to shipping. For the latest specifications and updates, visit www.STARDOM.com.tw or contact your sales representative.

For any inquiries about STARDOM products, or to receive the latest product manuals or firmware updates, please email us at: supporting@raidontek.com.

4